# **SIEMENS**

Data sheet 3RT2015-1AF01



CONTACTOR, AC-3, 3KW/400V, 1NO, AC110V, 50/60 HZ, 3-POLE, SZ S00 SCREW TERMINAL

product brand name	SIRIUS
Product designation	3RT2 contactor
General technical data:	
Size of contactor	S00
Product expansion	
<ul> <li>function module for communication</li> </ul>	No
Auxiliary switch	Yes
Insulation voltage	
Rated value	690 V
Surge voltage resistance Rated value	6 kV
maximum permissible voltage for safe isolation	400 V
between coil and main contacts acc. to EN 60947-1	
Protection class IP	
• on the front	IP20
of the terminal	IP20
Degree of pollution	3
Shock resistance	
at rectangular impulse	
— at AC	6,7g / 5 ms, 4,2g / 10 ms
• with sine pulse	
— at AC	10,5g / 5 ms, 6,6g / 10 ms
Mechanical service life (switching cycles)	
• of the contactor typical	30 000 000
<ul> <li>of the contactor with added electronics- compatible auxiliary switch block typical</li> </ul>	5 000 000

• of the contactor with added auxiliary switch block typical

10 000 000

Ambient conditions:	
Installation altitude at height above sea level	2 000 m
maximum	
Ambient temperature	
<ul><li>during operation</li></ul>	-25 +60 °C
during storage	-55 +80 °C
Main circuit:	
Number of NO contacts for main contacts	3
Number of NC contacts for main contacts	0
Operating voltage	
<ul> <li>at AC-3 Rated value maximum</li> </ul>	690 V
Operating current	
• at AC-1 at 400 V	
— at ambient temperature 40 °C Rated value	18 A
• at AC-1 up to 690 V	
— at ambient temperature 40 °C Rated value	18 A
— at ambient temperature 60 °C Rated value	16 A
• at AC-2 at 400 V Rated value	7 A
• at AC-3	
— at 400 V Rated value	7 A
— at 500 V Rated value	6 A
— at 690 V Rated value	4.9 A
Connectable conductor cross-section in main circuit at AC-1	
• at 60 °C minimum permissible	2.5 mm²
at 40 °C minimum permissible	2.5 mm <sup>2</sup>
Operating current for ≥ 200000 operating cycles at	
AC-4	
● at 400 V Rated value	2.6 A
● at 690 V Rated value	1.8 A
Operating current	
<ul><li>with 1 current path at DC-1</li></ul>	
— at 24 V Rated value	15 A
— at 110 V Rated value	1.5 A
— at 220 V Rated value	0.6 A
— at 440 V Rated value	0.42 A
— at 600 V Rated value	0.42 A
<ul> <li>with 2 current paths in series at DC-1</li> </ul>	
— at 24 V Rated value	15 A
— at 110 V Rated value	8.4 A

the operating current per conductor	
Active power loss at AC-3 at 400 V for rated value of	56 A 0.4 W
at 690 V Rated value  Thermal short-time current restricted to 10 s	56 A
at 400 V Rated value     at 600 V Rated value	1.15 kW 1.15 kW
AC-4	4 45 bW
— at 690 v Rated value  Operating power for ≥ 200000 operating cycles at	, ,,,,
— at 690 V Rated value	4 kW
— at 400 V Rated value	3 kW
— at 230 V Rated value	1.5 kW
• at AC-3	
at AC-2 at 400 V Rated value	3 kW
— at 690 V at 60 °C Rated value	18 kW
— at 690 V Rated value	19 kW
— at 400 V at 60 °C Rated value	10.5 kW
— at 400 V Rated value	11 kW
— at 230 V at 60 °C Rated value	6 kW
— at 230 V Rated value	6.3 kW
• at AC-1	
Operating power	
— at 600 V Rated value	0.14 A
— at 440 V Rated value	0.14 A
— at 24 V Rated value	15 A
— at 220 V Rated value	1.2 A
— at 110 V Rated value	15 A
with 3 current paths in series at DC-3 at DC-5	
— at 110 v Rated value  — at 24 V Rated value	15 A
- at 110 V Rated value	0.25 A
with 2 current paths in series at DC-3 at DC-5	• • • • • • • • • • • • • • • • • • • •
— at 24 V Rated value  — at 110 V Rated value	0.1 A
<ul><li>with 1 current path at DC-3 at DC-5</li><li>— at 24 V Rated value</li></ul>	15 A
Operating current	
— at 600 V Rated value	0.7 A
— at 440 V Rated value	0.9 A
— at 220 V Rated value	15 A
— at 110 V Rated value	15 A
— at 24 V Rated value	15 A
• with 3 current paths in series at DC-1	45.4
— at 600 V Rated value	0.5 A
— at 440 V Rated value	0.6 A
— at 220 V Rated value	1.2 A

No-load switching frequency		
• at AC	10 000 1/h	
Operating frequency		
■ at AC-1 maximum	1 000 1/h	
at AC-2 maximum	750 1/h	
• at AC-3 maximum	750 1/h	
● at AC-4 maximum	250 1/h	

Control circuit/ Control:	
Type of voltage of the control supply voltage	AC
Control supply voltage at AC	
● at 50 Hz Rated value	110 V
● at 60 Hz Rated value	110 V
Operating range factor control supply voltage rated	
value of the magnet coil at AC	
● at 50 Hz	0.8 1.1
● at 60 Hz	0.85 1.1
Apparent pick-up power of the magnet coil at AC	
● at 50 Hz	27 V·A
● at 60 Hz	31.7 V·A
Inductive power factor with closing power of the coil	
● at 50 Hz	0.8
● at 60 Hz	0.81
Apparent holding power of the magnet coil at AC	
● at 50 Hz	4.2 V·A
● at 60 Hz	4.8 V·A
Inductive power factor with the holding power of the	
coil	
● at 50 Hz	0.25
● at 60 Hz	0.25
Closing delay	
• at AC	9 35 ms
Arcing time	10 15 ms
Residual current of the electronics for control with signal <0>	
• at AC at 230 V maximum permissible	3 mA
• at DC at 24 V maximum permissible	10 mA

Auxiliary circuit:	
Number of NC contacts	
• for auxiliary contacts	
<ul> <li>instantaneous contact</li> </ul>	0
Number of NO contacts	
• for auxiliary contacts	

— instantaneous contact	1
Operating current at AC-12 maximum	10 A
Operating current at AC-15	
• at 230 V Rated value	10 A
at 400 V Rated value	3 A
● at 500 V Rated value	2 A
• at 690 V Rated value	1 A
Operating current at DC-12	
• at 24 V Rated value	10 A
• at 48 V Rated value	6 A
• at 60 V Rated value	6 A
• at 110 V Rated value	3 A
• at 125 V Rated value	2 A
• at 220 V Rated value	1 A
• at 600 V Rated value	0.15 A
Operating current at DC-13	
• at 24 V Rated value	10 A
• at 48 V Rated value	2 A
• at 60 V Rated value	2 A
• at 110 V Rated value	1 A
• at 125 V Rated value	0.9 A
at 220 V Rated value	0.3 A
- at ZZU v Matcu valud	
at 600 V Rated value	0.1 A
	0.1 A 1 faulty switching per 100 million (17 V, 1 mA)
at 600 V Rated value  Contact reliability of the auxiliary contacts	
at 600 V Rated value  Contact reliability of the auxiliary contacts	
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:	
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor	1 faulty switching per 100 million (17 V, 1 mA)
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value      at 600 V Rated value	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value      at 600 V Rated value  yielded mechanical performance [hp]	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value     at 600 V Rated value  yielded mechanical performance [hp]  for single-phase AC motor	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A 6.1 A
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value      at 600 V Rated value  yielded mechanical performance [hp]      for single-phase AC motor  — at 110/120 V Rated value	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A 6.1 A  0.25 hp
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value     at 600 V Rated value  yielded mechanical performance [hp]      for single-phase AC motor      at 110/120 V Rated value      at 230 V Rated value	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A 6.1 A  0.25 hp
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value      at 600 V Rated value  yielded mechanical performance [hp]      for single-phase AC motor      — at 110/120 V Rated value      — at 230 V Rated value      for three-phase AC motor	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A 6.1 A  0.25 hp 0.75 hp
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor     at 480 V Rated value     at 600 V Rated value  yielded mechanical performance [hp]     for single-phase AC motor     — at 110/120 V Rated value     — at 230 V Rated value     for three-phase AC motor     — at 200/208 V Rated value	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A 6.1 A  0.25 hp 0.75 hp  1.5 hp
at 600 V Rated value  Contact reliability of the auxiliary contacts  JL/CSA ratings:  Full-load current (FLA) for three-phase AC motor      at 480 V Rated value     at 600 V Rated value  yielded mechanical performance [hp]      for single-phase AC motor          — at 110/120 V Rated value          — at 230 V Rated value          for three-phase AC motor          — at 200/208 V Rated value          — at 220/230 V Rated value	1 faulty switching per 100 million (17 V, 1 mA)  4.8 A 6.1 A  0.25 hp 0.75 hp  1.5 hp 2 hp

## Short-circuit:

## Design of the fuse link

• for short-circuit protection of the main circuit

— with type of assignment 1 required

— with type of assignment 2 required

• for short-circuit protection of the auxiliary switch required

gL/gG LV HRC 3NA, DIAZED 5SB, NEOZED 5SE: 35 A gL/gG LV HRC 3NA, DIAZED 5SB, NEOZED 5SE: 20 A fuse gL/gG: 10 A

mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface
Mounting type	screw and snap-on mounting onto 35 mm standard mounting rai
	according to DIN EN 50022
<ul> <li>Side-by-side mounting</li> </ul>	Yes
Height	58 mm
Width	45 mm
Depth	73 mm
Required spacing	
<ul><li>with side-by-side mounting</li></ul>	
— forwards	0 mm
— Backwards	0 mm
— upwards	0 mm
— downwards	0 mm
— at the side	0 mm
<ul><li>for grounded parts</li></ul>	
— forwards	0 mm
— Backwards	0 mm
— upwards	0 mm
— at the side	6 mm
— downwards	0 mm
• for live parts	
— forwards	0 mm
— Backwards	0 mm
— upwards	0 mm
— downwards	0 mm
— at the side	6 mm

Connections/ Terminals:	
Type of electrical connection	
for main current circuit	screw-type terminals
<ul> <li>for auxiliary and control current circuit</li> </ul>	screw-type terminals
Type of connectable conductor cross-section	
• for main contacts	
<ul><li>— single or multi-stranded</li></ul>	2x (0,5 1,5 mm²), 2x (0,75 2,5 mm²), 2x 4 mm²
<ul> <li>finely stranded with core end processing</li> </ul>	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)

<ul> <li>for AWG conductors for main contacts</li> </ul>	2x (20 16), 2x (18 14), 2x 12
Type of connectable conductor cross-section	
<ul> <li>for auxiliary contacts</li> </ul>	
<ul><li>— single or multi-stranded</li></ul>	2x (0,5 1,5 mm²), 2x (0,75 2,5 mm²), 2x 4 mm²
<ul> <li>finely stranded with core end processing</li> </ul>	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
<ul> <li>for AWG conductors for auxiliary contacts</li> </ul>	2x (20 16), 2x (18 14), 2x 12

1 000 000
40 %
73 %
Yes; with 3RH29
20 y

# Certificates/ approvals:

#### **General Product Approval**

Functional Safety/Safety of Machinery Declaration of Conformity









Baumusterbescheini gung



#### **Test Certificates**

### **Shipping Approval**

<u>spezielle</u> Prüfbescheinigunge n Typprüfbescheinigu ng/Werkszeugnis

No.

ON SHIPPING







GL

# **Shipping Approval**











other

Umweltbestätigung

Bestätigungen

### other



### Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system)

http://www.siemens.com/industrymall

#### Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT20151AF01

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT20151AF01

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RT20151AF01&lang=en



